

Short Codes – SmartMobile Plus

First two digits “85” can be different per organisation. The following digits are always the same. Codes for FMU – Fixed & Mobile Unification- remain unchanged.

VoiceMail	Code
Corporate VoiceMail - (user needs to be in Corporate mode)	
Consult Corporate VoiceMail	8500
Consult VoiceMail other extension	8501 <extension>
Private Mobile VoiceMail - (linked to SIM card or mobile number)	
Consult and Settings	9123

Action	Code
Codes to be used from a mobile when in “Corporate” mode.	
Change pincode	8570
Department pickup	8573
Disable all call forwards	8579
Disable unconditional call forward	85794
Enable call forward	85791 <number>
Enable call forward on busy	85792 <number>
Enable call forward on busy to last number	85792
Enable call forward to last number	85791
Enable call forward to mobile	85793
Extension pickup	8572 <extension>
Group pickup	8572
Pum login (on Deskphone)	8580
Pum logout (on Deskphone)	8581
*Toggle Mobile active call to Desktop/ ConnectMe	8011

**for users with fixed & mobile unification (FMU)*

Status & Mode	Code
Change status (Office, Busy/DnD, Holiday, Telework, OoO)	8571
Change status other extension	8577 <extension>
*Check and change mode (Private, Corporate) w/voicepromt	8501
*Set Corporate mode	8502
*Set Private mode	8503
*Toggle from one to other	8504

**for users with fixed & mobile unification (FMU)*